

60 Watt P.A. Amplifier with FM Tuner & MP3 Ready CD Player

P60FACD 60W P.A. amplifier

Features

- 4 zoned 70 or 25V speaker outputs
- FM Tuner with 8-function CD player
- Telephone paging input and Music-on-hold output
- Individual volume control for each Mic input
- Front bass and treble controls
- Mic1 selectable priority paging
- UL & CSA listed



rear of unit

Specifications

| | |
|---------------------------|--|
| RMS Output Power..... | 60W |
| Max. Output Power..... | 90W |
| AC Power Consumption..... | 170W |
| Power Supply | AC 115V, 50Hz/60Hz |
| Zones..... | 4 |
| Speaker Outputs..... | 4/8/16 Ohms (non-zoned), 70/25V (zoned) |
| Other Outputs | Aux (RCA) |
| Inputs..... | 1 x AM Antenna (Press terminal), 1 x FM Antenna (BNC), 3 x Aux (Stereo RCA), 4 x Mic (XLR), 1 x TEL (Terminal) |
| Frequency Response | 60Hz ~ 15KHz (±3dB) |
| Tone Control | Bass ± 10dB, Treble ± 10dB |
| THD | Less than 1% @ 1KHz |
| Signal/Noise Ratio | >70dB |
| Controls | Volume for each Mic, Master Volume, Vox Volume, MoH Volume, Vox Selector, Tone, Source Selector, Zone Selector, Tuner and CD |
| Telephone | TEL in and MoH Out |
| Indicators..... | Tuner, CD, power, power level |
| Dimensions..... | 16.9" (W) x 3.5" (H) x 11.6" (D) |
| Weight | 21.4 lbs. |
| Listings | UL, cUL, CSA, CE, FCC |

Rack mounting kit available: **PBMRK2**